MINI AV-SENDER

Audio/video signal transmitter
with remote control repeater

5,8 GHz

L: 22,51 cm
H: 28,48 cm
P: 7,10 cm

MINI AV SENDER	Cod. 43000
Allows to transfer the wireless signal from an AV device(SAT,DTT,DVD etc) to a device (TV,Monitor,Speakers) in a different room	
Range of about 130 mt. (30 mt. Through walls)	
General	
Frequency	5.725GHz – 5.875GHz
Channel	7 selectable channels
Antenna	Patch array antenna
IR Remote Frequency	433.92MHz
IR Carrier Frequency	32 ~ 57KHz
Input /Output port	3.5mm AV phone jack
Power supply	DC 9V power adapter
Dimension	110 x 65 x 30 mm
Transmitter	
Supply Current	140mA ±10mA
Output Power	13dBm / 1dB (CE) 0dBm / 1dB (FCC)
Receiver IR Extender	
Receiving Sensitivity	-95dBm,min
IR LED Operation Range	2 Meters (min.)
External IR LED Port	2.5mm Mono Phone Jack
Receiver	
Supply Current	230mA ±20mA
Input Sensitivity	-85dBm, Typ.
Video Output	1VP-P , typ. (±0.2V)
Transmitter IR Extender	
RF Output Power	8dBm ±2dB (CE) 0dBm ±2dB (FCC) 0dBm ±2dB (FCC)
Sensor Range	5 Meters, min.
EAN	**8028626430003**

Jolly line by GBS

GBS Elettronica s.r.l
www.jollyline.it sales@gbs-elettronica.it
Link: http://www.gbs-elettronica.it/dwn/download.htm